

Ballroom Entrance Openings

1	Hollow Metal Frame	Ceco/Curries	16 Ga CR Steel - 6' x 8'
2	Stile & Rail Wood Door	Maiman	3' x 8'
8	Hinge	McKinney	T4A3786NRP - 4.5" x 4.5"
2	Exit Device	Adams Rite	3900-LR
1	Card Reader	VingCard	Remote Controller
2	Power Transfer	Securitron	EPT
2	Door Pulls	Rockwood	RM6060 x 36"
2	Door Closer	Norton	7500
2	Wall Magnet	Rixson	FM998
2	Kick Plate - Shaped	Rockwood	K1050F-4 - 8" x 34"
2	Wall Stop	Rockwood	406
1	Smoke Seal	Pemko	S88 x S772
1	Power Supply w/Battery	Adams Rite	PS-LR x BBK-LR
1	Power Supply w/Battery	Securitron	BPS24-1 x B-24-5

Operation: Authorized card inserted in reader retracts exit device latches allowing entry. Card reader maintains closed contact for maintained latch retraction. Next insertion of authorized card opens contact releasing latches and securing opening. Doors may be held open using wall magnets. Power supplies and wall magnets linked to building fire alarm system to provide positive latching in fire emergency.